

MOT-481600BLDC 48 Volt 1600 Watt Brushless DC Motor

Operating Voltage: 48 Volts DC

Rated Power: 1600 Watts



RPM: 4800

Phase Wires: 3 (Yellow, Green, Blue)

Phase Wire Terminals: 5.3mm ID Ring Terminals

Sensor Wires: 5 (Red, Black, Yellow, Green, Blue)

Sensor Wire Terminals: 2.8mm Wide Male Terminals

Motor Phase Wires		Yellow to Yellow Controller Phase U Wire Green to Green Controller Phase W Wire Blue to Blue Controller Phase V Wire
Motor Sensor Wires		Red to Red Controller Sensor Wire +5V Black to Black Controller Sensor Wire GND Yellow to Yellow Controller Sensor U Wire Green to Green Controller Sensor W Wire Blue to Blue Controller Sensor V Wire

